

PTZ Camera Joystick Keyboard Controller



Key Features:

- Adopt RS485, RS422, RS232 Multiple Interface Control Signals. Support to connect up to 255 cameras.
- Support PELCO-D, PELCO-P, VISCA control protocol.
- Metal shell, Computer keyboard button design.
- Adopt Three-dimensional joystick to control the speed of the camera.
- Control camera rotation, zoom, aperture, focus, and other camera settings.
- LCD display in English and Chinese, Real-time display of the working status of the decoder and matrix.
- Key sound prompt function.
- Unique control code learning function. Customers can modify the control code instructions by themselves.
- Any device on the RS485 bus can be set to a different protocol and baud rate.
- RS422 communication interface has automatic recovery function of short circuit overcurrent protection.
- The longest communication distance is up to 1200M (0.5MM twisted pair).



RS-232			RS-422				
2P	3P	5P	1	2	3	4	5
RXD	TXD	GND	Ta	Tb	Ra	Rb	GND



Specifications

Interfaces	RS232 Serial Port; RS232RS485 Half duplex, RS422 Full duplex,
Control Protocol	PELCO-D, PELCO-P, VISCA
Communication Baud Rate	2400bps, 4800bps, 9600bps, 19200bps
Joystick	Three-dimensional (Control: up, down, left, right, rotate)
Display Mode	LCD Blue Screen Display
Power Supply	DC12V±10%
Power Consumption	6W MAX
Working Temperature	-10℃~50℃
Storage Temperature	≅90%RH (No frosting)
Dimensions	320mm(L)×179.3mm(W)×106.4mm(H)

Dimension (unit:mm)

